

Results shown below are test results.  
TOSHIBA do not guarantee the operating behavior mentioned below. Toshiba will not accept claims for any damage caused by implementing the tested combination referred to in this document.

Dimmer Compatibility 2015-02-23	GU10					
	5,4 Watt LDR0527MU1EUD LDR0527WU1EUD LDR0530MU1EUD LDR0530WU1EUD LDR0540MU1EUD LDR0540WU1EUD	9 Watt LDR0927MU1EUD2 LDR0927WU1EUD2 LDR0930MU1EUD2 LDR0930WU1EUD2 LDR0940MU1EUD2 LDR0940WU1EUD2	4,5W LDP004D27M40DEU LDP004D30M40DEU LDP004D40M40DEU	7W LDP005D27M40DEU LDP005D27W40DEU LDP005D30M40DEU LDP005D30W40DEU LDP005D40M40DEU LDP005D40W40DEU	8W LDP006D27M40DEU LDP006D27W40DEU LDP006D30M40DEU LDP006D30W40DEU LDP006D40M40DEU LDP006D40W40DEU	5,5W LDP003D3040-EUC
ABB Busch Jäger Busch-Duro 2000 2200UJ-212	1-8 pcs., Setting LC1	1-10 pcs., Setting LC1				
ABB Busch Jäger 2250 D12 -600W			causes flickering	1-10 pcs.	1-10 pcs.	
ABB Busch Jäger 6513U-102 40-420W			1-8 pcs.	1-10 pcs.	1-10 pcs.	
Busch Jäger 6519U -550W			1-10 pcs.			
ABB Busch Jäger 6523U JGL-214 2-100VA	2-10 pcs., 1 sec. Leveling out	2-10 pcs., 1 sec. Leveling out		1-10 pcs.	1-10 pcs.	1-10 pcs.
Aurora AU-DSP 250 E14 -250W			1-4 pcs.	1-4 pcs.	1-4 pcs.	
Berker 2873 D2 20-500W				4-8 pcs., creates buzzing on dimmer	2-8 pcs., creates buzzing on dimmer	
Danlers DP1D250W E6 40-250W			1-4 pcs.	1-4 pcs.	1-4 pcs.	
Dimmax 520 S E-nr: 13 770 14 1-200W	1-10 pcs., Short flickering when switching on	1-10 pcs., Short flickering when switching on	1-10 pcs.	1-10 pcs.	1-10 pcs., creates buzzing in lamp	1-10 pcs., creates buzzing in lamp
Duwi 14386 60-300W			1-2 pcs.			
Elko RS16 300 GL 60-300W No 1471449						
Elko RS16 315 GLE SE 1363141 20-315W, TE		3-10 pcs.		8-10 pcs.	8-10 pcs.	7-10 pcs.
Elko RS dimmer SE 1363143 420GLE/I			5-10 pcs.	6-10 pcs.	6-10 pcs.	7-10 pcs.
Elko SE 1363146 600GLI						2-10 pcs.
Elko RS16 1000 GLE SE 1901526 40-1000W						
Elko RS16 400GLI SE 1363071						2-10 pcs.

Results shown below are test results.  
TOSHIBA do not guarantee the operating behavior mentioned below. Toshiba will not accept claims for any damage caused by implementing the tested combination referred to in this document.

**Dimmer  
Compatibility  
2015-02-23**

GU10						
5,4 Watt	9 Watt	4,5W	7W	8W	5,5W	
LDRC0527MU1EUD LDRC0527WU1EUD LDRC0530MU1EUD LDRC0530WU1EUD LDRC0540MU1EUD LDRC0540WU1EUD	LDRC0927MU1EUD2 LDRC0927WU1EUD2 LDRC0930MU1EUD2 LDRC0930WU1EUD2 LDRC0940MU1EUD2 LDRC0940WU1EUD2	LDP004D27M40DEU LDP004D30M40DEU LDP004D40M40DEU	LDP005D27M40DEU LDP005D27W40DEU LDP005D30M40DEU LDP005D30W40DEU LDP005D40M40DEU LDP005D40W40DEU	LDP006D27M40DEU LDP006D27W40DEU LDP006D30M40DEU LDP006D30W40DEU LDP006D40M40DEU LDP006D40W40DEU	LDP003D3040-EUC	
Elko RS16 630 GLE SE 136145 20-630W, TE			8-10 pcs.	8-10 pcs.	7-10 pcs.	
Elko RS16 200LED uni dimmer	1-7 pcs.	1-10 pcs.	1-10 pcs.		2-10 pcs.	
Eitako EUD61NPN-UC	1-8 pcs., Setting LC1	1-10 pcs., Setting LC1	1-10 pcs.	1-10 pcs., creates buzzing	1-10 pcs.	
Eitako EUD61NPN-230V		flickering when swithing on/off	1-10 pcs.	1-10 pcs., creates buzzing	1-10 pcs.	
Eitako EUD12D-UC		1-10 pcs.	1-10 pcs.	1-10 pcs., creates buzzing	1-10 pcs.	
Eitako EUD61M-UC				2-10 pcs.	2-10 pcs.	
Eitako EUD61NPS-400W						
Feller Edizio Due, Standard, FLF (Fertigapparate) 40300.RCxx			8-10 pcs.	8-10 pcs.	7-10 pcs.	
Feller Edizio Due, Standard, FLF (Fertigapparate) 40420.RLCxxx		5-10 pcs.	6-10 pcs.	6-10 pcs.	7-10 pcs.	
Feller Edizio Due, Standard, FLF (Fertigapparate) 40600.RLxxx					2-10 pcs.	
Feller Edizio Due, Standard, FLF (Fertigapparate) 40600.RCxxx			8-10 pcs.	8-10 pcs.	7-10 pcs.	
Feller Edizio Due, Standard, FLF (Fertigapparate) 40200.RCxxx	1-7 pcs.	1-10 pcs.	1-10 pcs.		2-10 pcs.	
GIRA 0307 00/101 20-525W		1-10 pcs.				
Hager EV 100 20-1000VA		4-10 pcs.	4-10 pcs.	3-10 pcs.	2-10 pcs.	
Hager EVN 004		3-10 pcs.	2-10 pcs.	2-10 pcs., creates buzzing	2-10 pcs.	
Hager EVN 012		4-10 pcs.	3-10 pcs.	4-10 pcs.	1-10 pcs.	
Jung 225 NV DE 20-500W		1-10 pcs.				
Jung 225T DE 20-525W		1-10 pcs.	1-10 pcs.	1-10 pcs.		

Results shown below are test results.  
TOSHIBA do not guarantee the operating behavior mentioned below. Toshiba will not accept claims for any damage caused by implementing the tested combination referred to in this document.

**Dimmer  
Compatibility  
2015-02-23**

GU10						
5,4 Watt	9 Watt	4,5W	7W	8W	5,5W	
LDR0527MU1EUD LDR0527WU1EUD LDR0530MU1EUD LDR0530WU1EUD LDR0540MU1EUD LDR0540WU1EUD	LDR0927MU1EUD2 LDR0927WU1EUD2 LDR0930MU1EUD2 LDR0930WU1EUD2 LDR0940MU1EUD2 LDR0940WU1EUD2	LDP004D27M40DEU LDP004D30M40DEU LDP004D40M40DEU	LDP005D27M40DEU LDP005D27W40DEU LDP005D30M40DEU LDP005D30W40DEU LDP005D40M40DEU LDP005D40W40DEU	LDP006D27M40DEU LDP006D27W40DEU LDP006D30M40DEU LDP006D30W40DEU LDP006D40M40DEU LDP006D40W40DEU	LDP003D3040-EUC	
Kopp 80,33 40-400W		1-10 pcs.				
Le Grand 0 670 82 600W		2-4 pcs.				
Le Grand 0 670 83 400W		1-10 pcs.	1-10 pcs.	1-10 pcs.		
Le Grand 0 670 84 400W			3-8 pcs.	1-10 pcs., flickering		
Le Grand 0 670 85 400W		1-10 pcs.	1-10 pcs.	1-10 pcs.		
Legrand Mosaic 0 784 07 3-75W			4-10 pcs.			
LICHTREGLER T38S 60-800W		1-10 pcs.				
Lichtregler T46S 20-315W		1-10 pcs.				
Merten rotary dimmer insert for inductive Load MEGS131 / 5132 / MEGS133-0000						2-10 pcs.
Merten MEGS134-0000 ELG174231 4-400W		1-7 pcs.	1-10 pcs.	1-10 pcs.		2-10 pcs.
Merten rotary dimmer insert MEGS136-0000		3-10 pcs., small dimming range for 1-2 pcs.		8-10 pcs.	8-10 pcs.	7-10 pcs.
Merten rotary dimmer insert MEGS137-0000		2-10 pcs., small dimming range for 1-2 pcs.		8-10 pcs.	8-10 pcs.	7-10 pcs.
Merten Universal-rotary dimmer insert MEGS138-0000			5-10 pcs.	6-10 pcs.	6-10 pcs.	7-10 pcs.
Merten Dimmer-insert 400GU 40-400W RL						2-10 pcs.
Peha 207913 60-300W		1-10 pcs.				

Results shown below are test results.

TOSHIBA do not guarantee the operating behavior mentioned below. Toshiba will not accept claims for any damage caused by implementing the tested combination referred to in this document.

**Dimmer  
Compatibility  
2015-02-23**

GU10						
5,4 Watt	9 Watt	4,5W	7W	8W	5,5W	
LDRC0527MU1EUD LDRC0527WU1EUD LDRC0530MU1EUD LDRC0530WU1EUD LDRC0540MU1EUD LDRC0540WU1EUD	LDRC0927MU1EUD2 LDRC0927WU1EUD2 LDRC0930MU1EUD2 LDRC0930WU1EUD2 LDRC0940MU1EUD2 LDRC0940WU1EUD2	LDP004D27M40DEU LDP004D30M40DEU LDP004D40M40DEU	LDP005D27M40DEU LDP005D27W40DEU LDP005D30M40DEU LDP005D30W40DEU LDP005D40M40DEU LDP005D40W40DEU	LDP006D27M40DEU LDP006D27W40DEU LDP006D30M40DEU LDP006D30W40DEU LDP006D40M40DEU LDP006D40W40DEU	LDP003D3040-EUC	

REV 002711 60-300W		1-10 pcs.				
RVE RVS 1000W		1-10 pcs.	1-10 pcs.	1-10 pcs.		
RVE RVT RV LED 500W						
Schneider Electric Trend CCTSE13011		5-10 pcs.	6-10 pcs.	6-10 pcs.	7-10 pcs.	
Schneider Electric Trend 315 RC CCTSE12011 CCTDE12001 5265518	3-10 pcs., small dimming range for 1-2 pcs.		8-10 pcs.	8-10 pcs.	7-10 pcs.	
Schneider Electric SS20511 SS30511 CCTDE11001 CCTDE11002 40,600W					2-10 pcs.	
Schneider Electric MGUX.511.xx 40-400W/VA WDE0002349					2-10 pcs.	
Schneider Electric Trend 20045602 SE 1370833 600W/VA	3-10 pcs., small dimming range for 1-2 pcs.		3-10 pcs.	3-10 pcs.	2-10 pcs.	
Schneider Electric Trend 630 RC CCTSE12111	2-10 pcs., small dimming range for 1-2 pcs.		8-10 pcs.	8-10 pcs.	7-10 pcs.	
Schneider Electric SBD200LED Uni.-rotary for LED Odace SSX0512	1-7 pcs.	1-10 pcs.	1-10 pcs.		2-10 pcs.	
Schneider Electric Unica Top 511 500W						
Siemens STC8 256 90-400W		1-2 pcs.				
Vadsbo tryckdimmer DRS 420-1 90-420W	3-10 pcs.		7-10 pcs.	3-10 pcs.		

Results shown below are test results.  
TOSHIBA do not guarantee the operating behavior mentioned below. Toshiba will not accept claims for any damage caused by implementing the tested combination referred to in this document.

Dimmer Compatibility 2015-02-23	E14			E27			PAR		
	Candle 6 Watt LD00627114100U	Candle/Golfball 4.5W LD0060276000U LD0060276000U LD0060276000U LD0060276000U LD0060276000U LD0060276000U	Candle/Golfball 6W LD0060276000U LD0060276000U LD00110271000U	7 Watt LD00100127100U LD00100124000U	10.5 Watt LD00100127100U	13 Watt LD00100127100U	PAR20 9 Watt LD0012776175U0 LD0012776175U0 LD0012776175U0	PAR30 14 Watt LD0012776175U0 LD0012776175U0 LD0012776175U0 LD0012776175U0 LD0012776175U0 LD0012776175U0 LD0012776175U0	PAR38 18.8 Watt LD0012776175U0 LD0012776175U0 LD0012776175U0 LD0012776175U0 LD0012776175U0 LD0012776175U0 LD0012776175U0
ABB Busch Zäger Busch Smart 2000 2200UJ 212	0-8 pcs. Setting LCI				0-10 pcs. creates noises	0-10 pcs. creates noises	0-10 pcs. Setting LCI	0-10 pcs. Setting LCI	0-10 pcs. Setting LCI
ABB Busch Zäger 2250 UJ2 600W	0-8 pcs.								
ABB Busch Zäger 8513U 102 40-420W									
Busch Zäger 8513U 550W									
ABB Busch Zäger 8523U (6U) 214 2-3000W	0-10 pcs.	0-10 pcs.	0-10 pcs.	0-10 pcs.	0-10 pcs.	0-10 pcs.	0-10 pcs. 1 second beeping out.	0-10 pcs. 1 second beeping out.	0-10 pcs. 1 second beeping out.
Arco AU 05P250 E14 250W									
Barker 2873 D2 20-500W									
Camden DP10250W E6 40-250W									
Commax F20 S E.nv. 13 1770 14 1-200W	0-10 pcs. Start flickering when switching on	0-10 pcs.	0-10 pcs.	0-10 pcs.	0-10 pcs.	0-10 pcs.	0-10 pcs.	0-10 pcs.	0-10 pcs.
Down F4386 60-900W									
Elco RS16 300 GL 80-300W No. 1471449									
Elco RS16 315 GLE 84 1363141 20-315W, TE			0-10 pcs.				0-10 pcs.	0-10 pcs.	0-10 pcs.
Elco RS dimmer EE 1363143 420GLE/L			0-10 pcs.						
Elco EE 1363146 600GLI		0-10 pcs.	0-10 pcs.	0-10 pcs. limited dimming range	0-10 pcs.	0-6 pcs.			
Elco RS16 1000 GLE 84 1363126 40-1000W							0-10 pcs.	0-10 pcs.	0-10 pcs.
Elco RS16 400GLI EE 1363071		0-10 pcs.	0-10 pcs.			0-10 pcs.			





Results shown below are test results.  
TOSHIBA do not guarantee the operating behavior mentioned below. Toshiba will not accept claims for any damage caused by implementing the tested combination referred to in this document.

Dimmer Compatibility 2015-02-23	E14			E27			PAR		
	Candle 6 Watt LDG09627114E140U	Candle/Golfball 4.5W LDG096027600EU LDG096027600EU LDG096027600EU LDG096027600EU LDG096027600EU	Candle/Golfball 6W LDG096027600EU LDG096027600EU LDG096027600EU	7 Watt LDG096027210B LDG096027210B	10.5 Watt LDG096027210B	13 Watt LDG096027210B	PAR20 9 Watt LDG0962714E7EUD LDG0962714E7EUD LDG0962714E7EUD	PAR30 14 Watt LDG0962714E7EUD LDG0962714E7EUD LDG0962714E7EUD LDG0962714E7EUD LDG0962714E7EUD LDG0962714E7EUD LDG0962714E7EUD	PAR38 18.8 Watt LDG0962714E7EUD LDG0962714E7EUD LDG0962714E7EUD LDG0962714E7EUD LDG0962714E7EUD LDG0962714E7EUD LDG0962714E7EUD LDG0962714E7EUD
REV 902711 50 300W									
REV RV5 1000W		3-8 pcs.	3-8 pcs.						
REV RV1 RV LED 600W									
Schneider Electric Triend CCT3E13011			0-10 pcs.						
Schneider Electric Triend 315 RC CCT3E12011 CCT3E13001 S365518			0-10 pcs.				0-10 pcs.	0-10 pcs.	0-10 pcs.
Schneider Electric S320511 S330511 CCT3E11001 CCT3E11002 40 400W		0-10 pcs.	0-10 pcs.	1-10 pcs. limited dimming range	0-10 pcs.	0-4 pcs.			
Schneider Electric MGLux 511 av 40 400W/VA W0E0002349		0-10 pcs.	0-10 pcs.						0-10 pcs.
Schneider Electric Triend 2004502 S31370833 400W/VA	0-10 pcs. limited dimming range	0-10 pcs.	0-10 pcs.	0-10 pcs.	0-10 pcs.	0-10 pcs.	0-10 pcs.	0-10 pcs.	0-10 pcs.
Schneider Electric Triend 630 RC CCT3E12111			0-10 pcs.				0-10 pcs.	0-10 pcs.	0-10 pcs.
Schneider Electric 86020LED LED - rotary for LED Dbase 350W/512		0-10 pcs.	0-10 pcs.	0-10 pcs.	0-10 pcs.	0-10 pcs.			
Schneider Electric Iuxica Top 511 600W		0-4 pcs.	0-4 pcs.						
Osram P752 246 50 400W									
Valibo Phydimmer 265 420-1 50 420W		0-10 pcs.					0-10 pcs.	0-10 pcs.	0-10 pcs.









