

Results shown below are test results.
TOSHIBA do not guarantee the operating behavior mentioned below. Toshiba will not accept claims for any damage caused by implementing the tested combination referred to in this document.

Dimmer Compatibility 2015-02-23	GU10					
	5,4 Watt LDR0527MU1EUD LDR0527WU1EUD LDR0530MU1EUD LDR0530WU1EUD LDR0540MU1EUD LDR0540WU1EUD	9 Watt LDR0927MU1EUD2 LDR0927WU1EUD2 LDR0930MU1EUD2 LDR0930WU1EUD2 LDR0940MU1EUD2 LDR0940WU1EUD2	4,5W LDP004D27M40DEU LDP004D30M40DEU LDP004D40M40DEU	7W LDP005D27M40DEU LDP005D27W40DEU LDP005D30M40DEU LDP005D30W40DEU LDP005D40M40DEU LDP005D40W40DEU	8W LDP006D27M40DEU LDP006D27W40DEU LDP006D30M40DEU LDP006D30W40DEU LDP006D40M40DEU LDP006D40W40DEU	5,5W LDP003D3040-EUC
ABB Busch Jäger Busch-Duro 2000 2200UJ-212	1-8 pcs., Setting LC1	1-10 pcs., Setting LC1				
ABB Busch Jäger 2250 D12 -600W			causes flickering	1-10 pcs.	1-10 pcs.	
ABB Busch Jäger 6513U-102 40-420W			1-8 pcs.	1-10 pcs.	1-10 pcs.	
Busch Jäger 6519U -550W			1-10 pcs.			
ABB Busch Jäger 6523U JGL-214 2-100VA	2-10 pcs., 1 sec. Leveling out	2-10 pcs., 1 sec. Leveling out		1-10 pcs.	1-10 pcs.	1-10 pcs.
Aurora AU-DSP 250 E14 -250W			1-4 pcs.	1-4 pcs.	1-4 pcs.	
Berker 2873 D2 20-500W				4-8 pcs., creates buzzing on dimmer	2-8 pcs., creates buzzing on dimmer	
Danlers DP1D250W E6 40-250W			1-4 pcs.	1-4 pcs.	1-4 pcs.	
Dimmax 520 S E-nr: 13 770 14 1-200W	1-10 pcs., Short flickering when switching on	1-10 pcs., Short flickering when switching on	1-10 pcs.	1-10 pcs.	1-10 pcs., creates buzzing in lamp	1-10 pcs., creates buzzing in lamp
Duwi 14386 60-300W			1-2 pcs.			
Elko RS16 300 GL 60-300W No 1471449						
Elko RS16 315 GLE SE 1363141 20-315W, TE		3-10 pcs.		8-10 pcs.	8-10 pcs.	7-10 pcs.
Elko RS dimmer SE 1363143 420GLE/I			5-10 pcs.	6-10 pcs.	6-10 pcs.	7-10 pcs.
Elko SE 1363146 600GLI						2-10 pcs.
Elko RS16 1000 GLE SE 1901526 40-1000W						
Elko RS16 400GLI SE 1363071						2-10 pcs.

Results shown below are test results.
TOSHIBA do not guarantee the operating behavior mentioned below. Toshiba will not accept claims for any damage caused by implementing the tested combination referred to in this document.

**Dimmer
Compatibility
2015-02-23**

GU10						
5,4 Watt	9 Watt	4,5W	7W	8W	5,5W	
LDRC0527MU1EUD LDRC0527WU1EUD LDRC0530MU1EUD LDRC0530WU1EUD LDRC0540MU1EUD LDRC0540WU1EUD	LDRC0927MU1EUD2 LDRC0927WU1EUD2 LDRC0930MU1EUD2 LDRC0930WU1EUD2 LDRC0940MU1EUD2 LDRC0940WU1EUD2	LDP004D27M40DEU LDP004D30M40DEU LDP004D40M40DEU	LDP005D27M40DEU LDP005D27W40DEU LDP005D30M40DEU LDP005D30W40DEU LDP005D40M40DEU LDP005D40W40DEU	LDP006D27M40DEU LDP006D27W40DEU LDP006D30M40DEU LDP006D30W40DEU LDP006D40M40DEU LDP006D40W40DEU	LDP003D3040-EUC	
Elko RS16 630 GLE SE 136145 20-630W, TE			8-10 pcs.	8-10 pcs.	7-10 pcs.	
Elko RS16 200LED uni dimmer	1-7 pcs.	1-10 pcs.	1-10 pcs.		2-10 pcs.	
Eitako EUD61NPN-UC	1-8 pcs., Setting LC1	1-10 pcs.	1-10 pcs.	1-10 pcs., creates buzzing	1-10 pcs.	
Eitako EUD61NPN-230V		flickering when swithing on/off	1-10 pcs.	1-10 pcs., creates buzzing	1-10 pcs.	
Eitako EUD12D-UC		1-10 pcs.	1-10 pcs.	1-10 pcs., creates buzzing	1-10 pcs.	
Eitako EUD61M-UC				2-10 pcs.	2-10 pcs.	
Eitako EUD61NPS-400W						
Feller Edizio Due, Standard, FLF (Fertigapparate) 40300.RCxx			8-10 pcs.	8-10 pcs.	7-10 pcs.	
Feller Edizio Due, Standard, FLF (Fertigapparate) 40420.RLCxxx		5-10 pcs.	6-10 pcs.	6-10 pcs.	7-10 pcs.	
Feller Edizio Due, Standard, FLF (Fertigapparate) 40600.RLxxx					2-10 pcs.	
Feller Edizio Due, Standard, FLF (Fertigapparate) 40600.RCxxx			8-10 pcs.	8-10 pcs.	7-10 pcs.	
Feller Edizio Due, Standard, FLF (Fertigapparate) 40200.RCxxx	1-7 pcs.	1-10 pcs.	1-10 pcs.		2-10 pcs.	
GIRA 0307 00/101 20-525W		1-10 pcs.				
Hager EV 100 20-1000VA		4-10 pcs.	4-10 pcs.	3-10 pcs.	2-10 pcs.	
Hager EVN 004		3-10 pcs.	2-10 pcs.	2-10 pcs., creates buzzing	2-10 pcs.	
Hager EVN 012		4-10 pcs.	3-10 pcs.	4-10 pcs.	1-10 pcs.	
Jung 225 NV DE 20-500W		1-10 pcs.				
Jung 225T DE 20-525W		1-10 pcs.	1-10 pcs.	1-10 pcs.		

Results shown below are test results.
TOSHIBA do not guarantee the operating behavior mentioned below. Toshiba will not accept claims for any damage caused by implementing the tested combination referred to in this document.

Dimmer Compatibility 2015-02-23	GU10					
	5,4 Watt	9 Watt	4,5W	7W	8W	5,5W
	LDR0527MU1EUD LDR0527WU1EUD LDR0530MU1EUD LDR0530WU1EUD LDR0540MU1EUD LDR0540WU1EUD	LDR0927MU1EUD2 LDR0927WU1EUD2 LDR0930MU1EUD2 LDR0930WU1EUD2 LDR0940MU1EUD2 LDR0940WU1EUD2	LDP004D27M40DEU LDP004D30M40DEU LDP004D40M40DEU	LDP005D27M40DEU LDP005D27W40DEU LDP005D30M40DEU LDP005D30W40DEU LDP005D40M40DEU LDP005D40W40DEU	LDP006D27M40DEU LDP006D27W40DEU LDP006D30M40DEU LDP006D30W40DEU LDP006D40M40DEU LDP006D40W40DEU	LDP003D3040-EUC
Kopp 80,33 40-400W			1-10 pcs.			
Le Grand 0 670 82 600W			2-4 pcs.			
Le Grand 0 670 83 400W			1-10 pcs.	1-10 pcs.	1-10 pcs.	
Le Grand 0 670 84 400W				3-8 pcs.	1-10 pcs., flickering	
Le Grand 0 670 85 400W			1-10 pcs.	1-10 pcs.	1-10 pcs.	
Legrand Mosaic 0 784 07 3-75W				4-10 pcs.		
LICHTREGLER T38S 60-800W			1-10 pcs.			
Lichtregler T46S 20-315W			1-10 pcs.			
Merten rotary dimmer insert for inductive Load MEGS131 / 5132 / MEGS133-0000						2-10 pcs.
Merten MEGS134-0000 ELG174231 4-400W	1-7 pcs.		1-10 pcs.	1-10 pcs.		2-10 pcs.
Merten rotary dimmer insert MEGS136-0000		3-10 pcs., small dimming range for 1-2 pcs.		8-10 pcs.	8-10 pcs.	7-10 pcs.
Merten rotary dimmer insert MEGS137-0000		2-10 pcs., small dimming range for 1-2 pcs.		8-10 pcs.	8-10 pcs.	7-10 pcs.
Merten Universal-rotary dimmer insert MEGS138-0000			5-10 pcs.	6-10 pcs.	6-10 pcs.	7-10 pcs.
Merten Dimmer-insert 400GU 40-400W RL						2-10 pcs.
Peha 207913 60-300W			1-10 pcs.			

Results shown below are test results.

TOSHIBA do not guarantee the operating behavior mentioned below. Toshiba will not accept claims for any damage caused by implementing the tested combination referred to in this document.

**Dimmer
Compatibility
2015-02-23**

GU10						
5,4 Watt	9 Watt	4,5W	7W	8W	5,5W	
LDRC0527MU1EUD LDRC0527WU1EUD LDRC0530MU1EUD LDRC0530WU1EUD LDRC0540MU1EUD LDRC0540WU1EUD	LDRC0927MU1EUD2 LDRC0927WU1EUD2 LDRC0930MU1EUD2 LDRC0930WU1EUD2 LDRC0940MU1EUD2 LDRC0940WU1EUD2	LDP004D27M40DEU LDP004D30M40DEU LDP004D40M40DEU	LDP005D27M40DEU LDP005D27W40DEU LDP005D30M40DEU LDP005D30W40DEU LDP005D40M40DEU LDP005D40W40DEU	LDP006D27M40DEU LDP006D27W40DEU LDP006D30M40DEU LDP006D30W40DEU LDP006D40M40DEU LDP006D40W40DEU	LDP003D3040-EUC	
REV 002711 60-300W		1-10 pcs.				
RVE RVS 1000W		1-10 pcs.	1-10 pcs.	1-10 pcs.		
RVE RVT RV LED 500W						
Schneider Electric Trend CCTSE13011		5-10 pcs.	6-10 pcs.	6-10 pcs.	7-10 pcs.	
Schneider Electric Trend 315 RC CCTSE12011 CCTDE12001 5265518	3-10 pcs., small dimming range for 1-2 pcs.		8-10 pcs.	8-10 pcs.	7-10 pcs.	
Schneider Electric SS20511 SS30511 CCTDE11001 CCTDE11002 40,600W					2-10 pcs.	
Schneider Electric MGUx.511.xx 40-400W/VA WDE0002349					2-10 pcs.	
Schneider Electric Trend 20045602 SE 1370833 600W/VA	3-10 pcs., small dimming range for 1-2 pcs.		3-10 pcs.	3-10 pcs.	2-10 pcs.	
Schneider Electric Trend 630 RC CCTSE12111	2-10 pcs., small dimming range for 1-2 pcs.		8-10 pcs.	8-10 pcs.	7-10 pcs.	
Schneider Electric SBD200LED Uni.-rotary for LED Odace SSX0512	1-7 pcs.	1-10 pcs.	1-10 pcs.		2-10 pcs.	
Schneider Electric Unica Top 511 500W						
Siemens STC8 256 90-400W		1-2 pcs.				
Vadsbo tryckdimmer DRS 420-1 90-420W	3-10 pcs.		7-10 pcs.	3-10 pcs.		

Results shown below are test results.
TOSHIBA do not guarantee the operating behavior mentioned below. Toshiba will not accept claims for any damage caused by implementing the tested combination referred to in this document.

Dimmer Compatibility 2015-02-23	E14			E27			PAR		
	Candle 6 Watt LD0006/7/11/41/102	Candle/Golfball 4.5W LD0006/2/7600EU LD0006/2/7600EU LD0006/2/7600EU LD0006/2/7600EU LD0006/2/7600EU LD0006/2/7600EU	Candle/Golfball 6W LD0006/2/7600EU LD0006/2/7600EU LD0011/02/7100EU	7 Watt LD0006/2/7100E LD0006/2/6400E	10.5 Watt LD0006/2/7100E	13 Watt LD0006/2/7100E	PAR20 9 Watt LD0009/2/76W/7EUD LD0009/2/76W/7EUD LD0009/2/66W/7EUD	PAR30 14 Watt LD0012/2/76W/7EUD LD0012/2/76W/7EUD LD0012/2/76W/7EUD LD0012/2/76W/7EUD LD0012/2/76W/7EUD LD0012/2/76W/7EUD LD0012/2/76W/7EUD LD0012/2/76W/7EUD LD0012/2/76W/7EUD LD0012/2/76W/7EUD	PAR38 18.8 Watt LD0012/2/76W/7EUD LD0012/2/76W/7EUD LD0012/2/76W/7EUD LD0012/2/76W/7EUD LD0012/2/76W/7EUD LD0012/2/76W/7EUD LD0012/2/76W/7EUD LD0012/2/76W/7EUD LD0012/2/76W/7EUD LD0012/2/76W/7EUD
ABB Busch Zäger Busch Smart 2000 2200UJ 212	0-8 pcs. Setting LCI				0-10 pcs. creates noises	0-10 pcs. creates noises	0-10 pcs. Setting LCI	0-10 pcs. Setting LCI	0-10 pcs. Setting LCI
ABB Busch Zäger 2250 UJ2 600W	0-8 pcs.								
ABB Busch Zäger R513U 102 40-420W									
Busch Zäger R513U 550W									
ABB Busch Zäger R523U (6U) 214 2-3000W	0-10 pcs.	0-10 pcs.	0-10 pcs.	0-10 pcs.	0-10 pcs.	0-10 pcs.	0-10 pcs. 1 second beeping out.	0-10 pcs. 1 second beeping out.	0-10 pcs. 1 second beeping out.
Arco AU 05P250 E14 250W									
Barker 2873 D2 20-500W									
Camden DP10250W E6 40-250W									
Commax F20 S E.nv. 13 770 14 1-200W	0-10 pcs. Start flickering when switching on	0-10 pcs.	0-10 pcs.	0-10 pcs.	0-10 pcs.	0-10 pcs.	0-10 pcs.	0-10 pcs.	0-10 pcs.
Down F4386 60-900W									
Elco R516 300 GL R50-300W No 1471449									
Elco R516 315 GLE R5 1363141 20-315W, TE			0-10 pcs.				0-10 pcs.	0-10 pcs.	0-10 pcs.
Elco R5 dimmer EE 1363143 420GLE/L			0-10 pcs.						
Elco EE 1363146 600GL		0-10 pcs.	0-10 pcs.	0-10 pcs. limited dimming range	0-10 pcs.	0-6 pcs.			
Elco R516 1000 GLE R5 1363126 40-1000W							0-10 pcs.	0-10 pcs.	0-10 pcs.
Elco R516 400GL EE 1363071		0-10 pcs.	0-10 pcs.			0-10 pcs.			

Results shown below are test results.
TOSHIBA do not guarantee the operating behavior mentioned below. Toshiba will not accept claims for any damage caused by implementing the tested combination referred to in this document.

Dimmer Compatibility 2015-02-23	E14			E27			PAR			
	Candle 6 Watt	Candle/Golfball 4.5W	Candle/Golfball 6W	7 Watt	10.5 Watt	13 Watt	PAR20 9 Watt	PAR30 14 Watt	PAR38 18.8 Watt	
REV 902711 50 300W	LDG09627114E14U LDG09627114E14U LDG09627114E14U LDG09627114E14U LDG09627114E14U	LDG09627114E14U LDG09627114E14U LDG09627114E14U LDG09627114E14U LDG09627114E14U	LDG09627114E14U LDG09627114E14U LDG09627114E14U LDG09627114E14U LDG09627114E14U	LDG09627114E14U LDG09627114E14U LDG09627114E14U LDG09627114E14U LDG09627114E14U	LDG09627114E14U LDG09627114E14U LDG09627114E14U LDG09627114E14U LDG09627114E14U	LDG09627114E14U LDG09627114E14U LDG09627114E14U LDG09627114E14U LDG09627114E14U	LDG09627114E14U LDG09627114E14U LDG09627114E14U LDG09627114E14U LDG09627114E14U	LDG09627114E14U LDG09627114E14U LDG09627114E14U LDG09627114E14U LDG09627114E14U	LDG09627114E14U LDG09627114E14U LDG09627114E14U LDG09627114E14U LDG09627114E14U	LDG09627114E14U LDG09627114E14U LDG09627114E14U LDG09627114E14U LDG09627114E14U
REV RV5 1000W		0-8 pcs.	0-8 pcs.							
REV RV1 RV LED 600W										
Schneider Electric Triend CCT3E13011			0-10 pcs.							
Schneider Electric Triend 315 RC CCT3E12011 CCT3E13001 S365518			0-10 pcs.				0-10 pcs.	0-10 pcs.	0-10 pcs.	0-10 pcs.
Schneider Electric S320511 S330511 CCT3E11001 CCT3E11002 40 400W		0-10 pcs.	0-10 pcs.	0-10 pcs. limited dimming range	0-10 pcs.	0-10 pcs.				
Schneider Electric MGLux 511 av 40 400W/VA W0E000349		0-10 pcs.	0-10 pcs.				0-10 pcs.			
Schneider Electric Triend 2004502 S3170833 400W/VA	0-10 pcs. limited dimming range	0-10 pcs.	0-10 pcs.	0-10 pcs.	0-10 pcs.	0-10 pcs.	0-10 pcs.	0-10 pcs.	0-10 pcs.	0-10 pcs.
Schneider Electric Triend 630 RC CCT3E12111			0-10 pcs.				0-10 pcs.	0-10 pcs.	0-10 pcs.	0-10 pcs.
Schneider Electric S602062D 10W - rotary for LED Dibase S506512		0-10 pcs.	0-10 pcs.	0-10 pcs.	0-10 pcs.	0-10 pcs.				
Schneider Electric Icnica Top 511 600W		0-4 pcs.	0-4 pcs.							
Osram P752 246 50 400W										
Valibo Phydimmer 265 420-1 50 420W		0-10 pcs.					0-10 pcs.	0-10 pcs.	0-10 pcs.	0-10 pcs.

Results shown below are test results.
TOSHIBA do not guarantee the operating behavior mentioned below. Toshiba will not accept claims for any damage caused by implementing the tested combination referred to in this document.

		GUS.3		
		4.6W	6.5W	7.5W
Dimmer Compatibility 2015-02-23	LDM003A27M30DEU	LDM004A27M30DEU	LDM005A27M30DEU	
	LDM003A30M30DEU	LDM004A30M30DEU	LDM005A27M30DEU	
	LDM003A40M30DEU	LDM004A40M30DEU	LDM005A30M30DEU	
			LDM005A30M30DEU	
Jung 225 NV DE 20-500W	Relco ICE60 OSRAM HTM70 VS EST105			
Jung 225T DE 20-525W	Relco ICE60 OSRAM HTM70 VS EST105			
Kopp 80.33 40-400W	Relco ICE60 OSRAM HTM70 VS EST105			
Le Grand 0 670 82 600W	Relco ICE60 OSRAM HTM70 VS EST105			
Le Grand 0 670 83 400W	Relco ICE60 OSRAM HTM70 VS EST105			
Le Grand 0 670 84 400W	Relco ICE60 OSRAM HTM70 VS EST105			
Le Grand 0 670 85 400W	Relco ICE60 OSRAM HTM70 VS EST105			
Legrand Mosaic 0 784 07 3-75W	Relco ICE60 OSRAM HTM70 VS EST105			
LICHTREGLER T385 60-800W	Relco ICE60 OSRAM HTM70 VS EST105			
Lichtregler T465 20-315W	Relco ICE60 OSRAM HTM70 VS EST105			
Merten rotary dimmer insert for inductive Load MEGS131 / 5132 / MEGS133-0000	Relco ICE60 OSRAM HTM70 VS EST105			
Merten MEGS134-0000 ELG174231 4-400W	Relco ICE60 OSRAM HTM70 VS EST105			
Merten rotary dimmer insert MEGS136-0000	Relco ICE60 OSRAM HTM70 VS EST105			
Merten rotary dimmer insert MEGS137-0000	Relco ICE60 OSRAM HTM70 VS EST105			
Merten Universal-rotary dimmer insert MEGS138-0000	Relco ICE60 OSRAM HTM70 VS EST105			
Merten Dimmer-insert 400GU 40-400W RL	Relco ICE60 OSRAM HTM70 VS EST105			

