

Results shown below are test results.
TOSHIBA do not guarantee the operating behavior mentioned below. Toshiba will not accept claims for any damage caused by implementing the tested combination referred to in this document.

| Dimmer Compatibility 2015-02-23 | GU10 | | | | | |
|---|--|--|---|--|--|---------------------------------------|
| | 5,4 Watt LDR0527MU1EUD LDR0527WU1EUD LDR0530MU1EUD LDR0530WU1EUD LDR0540MU1EUD LDR0540WU1EUD | 9 Watt LDR0927MU1EUD2 LDR0927WU1EUD2 LDR0930MU1EUD2 LDR0930WU1EUD2 LDR0940MU1EUD2 LDR0940WU1EUD2 | 4,5W LDP004D27M40DEU LDP004D30M40DEU LDP004D40M40DEU | 7W LDP005D27M40DEU LDP005D27W40DEU LDP005D30M40DEU LDP005D30W40DEU LDP005D40M40DEU LDP005D40W40DEU | 8W LDP006D27M40DEU LDP006D27W40DEU LDP006D30M40DEU LDP006D30W40DEU LDP006D40M40DEU LDP006D40W40DEU | 5,5W LDP003D3040-EUC |
| ABB Busch Jäger Busch-Duro 2000 2200UJ-212 | 1-8 pcs., Setting LC1 | 1-10 pcs., Setting LC1 | | | | |
| ABB Busch Jäger 2250 D12 -600W | | | causes flickering | 1-10 pcs. | 1-10 pcs. | |
| ABB Busch Jäger 6513U-102 40-420W | | | 1-8 pcs. | 1-10 pcs. | 1-10 pcs. | |
| Busch Jäger 6519U -550W | | | 1-10 pcs. | | | |
| ABB Busch Jäger 6523U JGL-214 2-100WA | 2-10 pcs., 1 sec. Leveling out | 2-10 pcs., 1 sec. Leveling out | | 1-10 pcs. | 1-10 pcs. | 1-10 pcs. |
| Aurora AU-DSP 250 E14 -250W | | | 1-4 pcs. | 1-4 pcs. | 1-4 pcs. | |
| Berker 2873 D2 20-500W | | | | 4-8 pcs., creates buzzing on dimmer | 2-8 pcs., creates buzzing on dimmer | |
| Danlers DP1D250W E6 40-250W | | | 1-4 pcs. | 1-4 pcs. | 1-4 pcs. | |
| Dimmax 520 S E-nr: 13 770 14 1-200W | 1-10 pcs., Short flickering when switching on | 1-10 pcs., Short flickering when switching on | 1-10 pcs. | 1-10 pcs. | 1-10 pcs., creates buzzing in lamp | 1-10 pcs., creates buzzing in lamp |
| Duwi 14386 60-300W | | | 1-2 pcs. | | | |
| Elko RS16 300 GL 60-300W No 1471449 | | | | | | |
| Elko RS16 315 GLE SE 1363141 20-315W, TE | | 3-10 pcs. | | 8-10 pcs. | 8-10 pcs. | 7-10 pcs. |
| Elko RS dimmer SE 1363143 420GLE/I | | | 5-10 pcs. | 6-10 pcs. | 6-10 pcs. | 7-10 pcs. |
| Elko SE 1363146 600GLI | | | | | | 2-10 pcs. |
| Elko RS16 1000 GLE SE 1901526 40-1000W | | | | | | |
| Elko RS16 400GLI SE 1363071 | | | | | | 2-10 pcs. |

Results shown below are test results.
TOSHIBA do not guarantee the operating behavior mentioned below. Toshiba will not accept claims for any damage caused by implementing the tested combination referred to in this document.

**Dimmer
Compatibility
2015-02-23**

| GU10 | | | | | | |
|--|--|---|--|--|-----------------|--|
| 5,4 Watt | 9 Watt | 4,5W | 7W | 8W | 5,5W | |
| LDRC0527MU1EUD LDRC0527WU1EUD LDRC0530MU1EUD LDRC0530WU1EUD LDRC0540MU1EUD LDRC0540WU1EUD | LDRC0927MU1EUD2 LDRC0927WU1EUD2 LDRC0930MU1EUD2 LDRC0930WU1EUD2 LDRC0940MU1EUD2 LDRC0940WU1EUD2 | LDP004D27M40DEU LDP004D30M40DEU LDP004D40M40DEU | LDP005D27M40DEU LDP005D27W40DEU LDP005D30M40DEU LDP005D30W40DEU LDP005D40M40DEU LDP005D40W40DEU | LDP006D27M40DEU LDP006D27W40DEU LDP006D30M40DEU LDP006D30W40DEU LDP006D40M40DEU LDP006D40W40DEU | LDP003D3040-EUC | |
| Elko RS16 630 GLE SE 136145 20-630W, TE | | | 8-10 pcs. | 8-10 pcs. | 7-10 pcs. | |
| Elko RS16 200LED uni dimmer | 1-7 pcs. | 1-10 pcs. | 1-10 pcs. | | 2-10 pcs. | |
| Eitako EUD61NPN-UC | 1-8 pcs., Setting LC1 | 1-10 pcs. | 1-10 pcs. | 1-10 pcs., creates buzzing | 1-10 pcs. | |
| Eitako EUD61NPN-230V | | flickering when swithing on/off | 1-10 pcs. | 1-10 pcs., creates buzzing | 1-10 pcs. | |
| Eitako EUD12D-UC | | 1-10 pcs. | 1-10 pcs. | 1-10 pcs., creates buzzing | 1-10 pcs. | |
| Eitako EUD61M-UC | | | | 2-10 pcs. | 2-10 pcs. | |
| Eitako EUD61NPS-400W | | | | | | |
| Feller Edizio Due, Standard, FLF (Fertigapparate) 40300.RCxx | | | 8-10 pcs. | 8-10 pcs. | 7-10 pcs. | |
| Feller Edizio Due, Standard, FLF (Fertigapparate) 40420.RLCxxx | | 5-10 pcs. | 6-10 pcs. | 6-10 pcs. | 7-10 pcs. | |
| Feller Edizio Due, Standard, FLF (Fertigapparate) 40600.RLxxx | | | | | 2-10 pcs. | |
| Feller Edizio Due, Standard, FLF (Fertigapparate) 40600.RCxxx | | | 8-10 pcs. | 8-10 pcs. | 7-10 pcs. | |
| Feller Edizio Due, Standard, FLF (Fertigapparate) 40200.RCxxx | 1-7 pcs. | 1-10 pcs. | 1-10 pcs. | | 2-10 pcs. | |
| GIRA 0307 00/101 20-525W | | 1-10 pcs. | | | | |
| Hager EV 100 20-1000VA | | 4-10 pcs. | 4-10 pcs. | 3-10 pcs. | 2-10 pcs. | |
| Hager EVN 004 | | 3-10 pcs. | 2-10 pcs. | 2-10 pcs., creates buzzing | 2-10 pcs. | |
| Hager EVN 012 | | 4-10 pcs. | 3-10 pcs. | 4-10 pcs. | 1-10 pcs. | |
| Jung 225 NV DE 20-500W | | 1-10 pcs. | | | | |
| Jung 225T DE 20-525W | | 1-10 pcs. | 1-10 pcs. | 1-10 pcs. | | |

Results shown below are test results.
TOSHIBA do not guarantee the operating behavior mentioned below. Toshiba will not accept claims for any damage caused by implementing the tested combination referred to in this document.

**Dimmer
Compatibility
2015-02-23**

| GU10 | | | | | | |
|--|--|---|--|--|-----------------|-----------|
| 5,4 Watt | 9 Watt | 4,5W | 7W | 8W | 5,5W | |
| LDR0527MU1EUD LDR0527WU1EUD LDR0530MU1EUD LDR0530WU1EUD LDR0540MU1EUD LDR0540WU1EUD | LDR0927MU1EUD2 LDR0927WU1EUD2 LDR0930MU1EUD2 LDR0930WU1EUD2 LDR0940MU1EUD2 LDR0940WU1EUD2 | LDP004D27M40DEU LDP004D30M40DEU LDP004D40M40DEU | LDP005D27M40DEU LDP005D27W40DEU LDP005D30M40DEU LDP005D30W40DEU LDP005D40M40DEU LDP005D40W40DEU | LDP006D27M40DEU LDP006D27W40DEU LDP006D30M40DEU LDP006D30W40DEU LDP006D40M40DEU LDP006D40W40DEU | LDP003D3040-EUC | |
| Kopp 80,33 40-400W | | 1-10 pcs. | | | | |
| Le Grand 0 670 82 600W | | 2-4 pcs. | | | | |
| Le Grand 0 670 83 400W | | 1-10 pcs. | 1-10 pcs. | 1-10 pcs. | | |
| Le Grand 0 670 84 400W | | | 3-8 pcs. | 1-10 pcs., flickering | | |
| Le Grand 0 670 85 400W | | 1-10 pcs. | 1-10 pcs. | 1-10 pcs. | | |
| Legrand Mosaic 0 784 07 3-75W | | | 4-10 pcs. | | | |
| LICHTREGLER T38S 60-800W | | 1-10 pcs. | | | | |
| Lichtregler T46S 20-315W | | 1-10 pcs. | | | | |
| Merten rotary dimmer insert for inductive Load MEGS131 / 5132 / MEGS133-0000 | | | | | | 2-10 pcs. |
| Merten MEGS134-0000 ELG174231 4-400W | | 1-7 pcs. | 1-10 pcs. | 1-10 pcs. | | 2-10 pcs. |
| Merten rotary dimmer insert MEGS136-0000 | | 3-10 pcs., small dimming range for 1-2 pcs. | | 8-10 pcs. | 8-10 pcs. | 7-10 pcs. |
| Merten rotary dimmer insert MEGS137-0000 | | 2-10 pcs., small dimming range for 1-2 pcs. | | 8-10 pcs. | 8-10 pcs. | 7-10 pcs. |
| Merten Universal-rotary dimmer insert MEGS138-0000 | | | 5-10 pcs. | 6-10 pcs. | 6-10 pcs. | 7-10 pcs. |
| Merten Dimmer-insert 400GU 40-400W RL | | | | | | 2-10 pcs. |
| Peha 207913 60-300W | | 1-10 pcs. | | | | |

Results shown below are test results.

TOSHIBA do not guarantee the operating behavior mentioned below. Toshiba will not accept claims for any damage caused by implementing the tested combination referred to in this document.

**Dimmer
Compatibility
2015-02-23**

| GU10 | | | | | | |
|--|--|---|--|--|-----------------|--|
| 5,4 Watt | 9 Watt | 4,5W | 7W | 8W | 5,5W | |
| LDRC0527MU1EUD LDRC0527WU1EUD LDRC0530MU1EUD LDRC0530WU1EUD LDRC0540MU1EUD LDRC0540WU1EUD | LDRC0927MU1EUD2 LDRC0927WU1EUD2 LDRC0930MU1EUD2 LDRC0930WU1EUD2 LDRC0940MU1EUD2 LDRC0940WU1EUD2 | LDP004D27M40DEU LDP004D30M40DEU LDP004D40M40DEU | LDP005D27M40DEU LDP005D27W40DEU LDP005D30M40DEU LDP005D30W40DEU LDP005D40M40DEU LDP005D40W40DEU | LDP006D27M40DEU LDP006D27W40DEU LDP006D30M40DEU LDP006D30W40DEU LDP006D40M40DEU LDP006D40W40DEU | LDP003D3040-EUC | |

| | | | | | | |
|---|--|-----------|-----------|-----------|-----------|--|
| REV 002711 60-300W | | 1-10 pcs. | | | | |
| RVE RVS 1000W | | 1-10 pcs. | 1-10 pcs. | 1-10 pcs. | | |
| RVE RVT RV LED 500W | | | | | | |
| Schneider Electric Trend CCTSE13011 | | 5-10 pcs. | 6-10 pcs. | 6-10 pcs. | 7-10 pcs. | |
| Schneider Electric Trend 315 RC CCTSE12011 CCTDE12001 5265518 | 3-10 pcs., small dimming range for 1-2 pcs. | | 8-10 pcs. | 8-10 pcs. | 7-10 pcs. | |
| Schneider Electric SS20511 SS30511 CCTDE11001 CCTDE11002 40,600W | | | | | 2-10 pcs. | |
| Schneider Electric MGUx.511.xx 40-400W/VA WDE0002349 | | | | | 2-10 pcs. | |
| Schneider Electric Trend 20045602 SE 1370833 600W/VA | 3-10 pcs., small dimming range for 1-2 pcs. | | 3-10 pcs. | 3-10 pcs. | 2-10 pcs. | |
| Schneider Electric Trend 630 RC CCTSE12111 | 2-10 pcs., small dimming range for 1-2 pcs. | | 8-10 pcs. | 8-10 pcs. | 7-10 pcs. | |
| Schneider Electric SBD200LED Uni.-rotary for LED Odace SSX0512 | 1-7 pcs. | 1-10 pcs. | 1-10 pcs. | | 2-10 pcs. | |
| Schneider Electric Unica Top 511 500W | | | | | | |
| Siemens STC8 256 90-400W | | 1-2 pcs. | | | | |
| Vadsbo tryckdimmer DRS 420-1 90-420W | 3-10 pcs. | | 7-10 pcs. | 3-10 pcs. | | |

Results shown below are test results.
TOSHIBA do not guarantee the operating behavior mentioned below. Toshiba will not accept claims for any damage caused by implementing the tested combination referred to in this document.

| Dimmer Compatibility 2015-02-23 | E14 | | | E27 | | | PAR | | |
|---|------------------------------------|--|--|--|----------------------------|--------------------------|---|---|--|
| | Candle 6 Watt LDG09627114E140U | Candle/Golfball 4.5W LDG096027600EU LDG096027600EU LDG096027600EU LDG096027600EU LDG096027600EU | Candle/Golfball 6W LDG096027600EU LDG096027600EU LDG096027600EU | 7 Watt LDG096027210B LDG096027210B | 10.5 Watt LDG096027210B | 13 Watt LDG096027210B | PAR20 9 Watt LDG0962714E7E14 LDG0962714E7E14 LDG0962714E7E14 | PAR30 14 Watt LDG0962714E7E14 LDG0962714E7E14 LDG0962714E7E14 LDG0962714E7E14 LDG0962714E7E14 LDG0962714E7E14 LDG0962714E7E14 LDG0962714E7E14 | PAR38 18.8 Watt LDG0962714E7E14 LDG0962714E7E14 LDG0962714E7E14 LDG0962714E7E14 LDG0962714E7E14 LDG0962714E7E14 LDG0962714E7E14 LDG0962714E7E14 LDG0962714E7E14 |
| REV 902711 50 300W | | | | | | | | | |
| REV RV5 1000W | | 3-8 pcs. | 3-8 pcs. | | | | | | |
| REV RV1 RV LED 600W | | | | | | | | | |
| Schneider Electric Triend CCT3E13011 | | | 0-10 pcs. | | | | | | |
| Schneider Electric Triend 315 RC CCT3E12011 CCT3E13001 S365518 | | | 0-10 pcs. | | | | 0-10 pcs. | 0-10 pcs. | 0-10 pcs. |
| Schneider Electric S320511 S330511 CCT3E11001 CCT3E11002 40 400W | | 0-10 pcs. | 0-10 pcs. | 1-10 pcs. limited dimming range | 0-10 pcs. | 0-4 pcs. | | | |
| Schneider Electric MGLux 511 av 40 400W/VA W0E0002349 | | 0-10 pcs. | 0-10 pcs. | | | 0-10 pcs. | | | |
| Schneider Electric Triend 2004502 S31370833 400W/VA | 0-10 pcs. limited dimming range | 0-10 pcs. | 0-10 pcs. | 0-10 pcs. | 0-10 pcs. | 0-10 pcs. | 0-10 pcs. | 0-10 pcs. | 0-10 pcs. |
| Schneider Electric Triend 630 RC CCT3E12111 | | | 0-10 pcs. | | | | 0-10 pcs. | 0-10 pcs. | 0-10 pcs. |
| Schneider Electric 86020LED 10W - rotary for LED Dibase 55W/512 | | 0-10 pcs. | 0-10 pcs. | 0-10 pcs. | 0-10 pcs. | 0-10 pcs. | | | |
| Schneider Electric Ionica Top 511 600W | | 0-4 pcs. | 0-4 pcs. | | | | | | |
| Demant P152 216 50 400W | | | | | | | | | |
| Valibo Phydimmer 265 420-1 50 420W | | 0-10 pcs. | | | | | 0-10 pcs. | 0-10 pcs. | 0-10 pcs. |

