



Charger & Maintainer 6V/12V – 1,5 Amp

EAN : 542503 853128 2

SKU : BXAE00021

- Charge & maintenance functions
- Maximum current 1,5 Amp
- Suitable for 6V/12V batteries
- Manual voltage selection
- No battery removal required
- For all types of lead-acid batteries
- Direct plug-in (wall mounted)
- Supplied with clamps and eyelets



SPECIFICATIONS

INPUT	Voltage	220 - 240 Volt AC 50 - 60Hz	
	Plug	EU	Type Standard
OUTPUT	Nominal Voltage	6V - 12V	Max Output 1.5A
	Cable length	1,5m + 0,5m clamps cable and O-rings cable	
	Terminals	Clamps and O-rings	
CAPACITY	Charge	2 - 30 Ah	Maintain 2 - 70 Ah
	Recovery	YES	
	Compatibility	Lead Acid battery : AGM , GEL , VLRA , WET , LIQUID	
INTERFACE	LED	Charging status - Error Indicator	
	MMI	Output voltage manual selection	
CERTIFICATION	CE EN60335 - 2 - 29 - LVD - EMC - RoHS		

SKU	EAN code	5425038 53128 2			
	Length	129mm	Width	103mm	Height 132mm
	Gross weight	480gr	Net weight	360gr	
Carton box	EAN code	2 5425038 53128 6			
	Length	342mm	Width	281mm	Height 149mm
	Gross weight	3,20kg	Net weight	2,13kg	
	Qty of SKUs per carton box	6			
PALLET	EAN code	4 5425038 53128 0			
	Length	120cm	Width	80cm	Height 135cm
	Gross weight	230kg	Net weight	142kg	
	Carton per layer	8	Qty of layers	8	Cartons per pallet 64
	Qty SKUs per pallet	384			
	type of pallet	Plywood pallet			