



App Remote Monitor

Smart SOS Call Button can be monitored through your existing Wi-Fi network via the free *Smart Life* or *Megos Smart Home* app.





Smart Life

Megos Smart Home

Download the free APP from the App Store or Google Play store.





System



Push Notification



Mountable



Rechargeable Battery

120 mAh

IP20



Emergency Button

Convenient for patient/elderly/handicapped/ sick who is seeking attention; also can be mounted under shop's counter as SOS button.



Remote Monitor from Anywhere

When button is pressed, it will send a push notification to your phone immediately, anywhere you are.



Security Automation

Connect with other LogiLink Smart products like Siren Alarm (SH0110) and IP Camera (SH0117) in automations to create a safer environment.

Specifications:

Wireless Standard	IEEE 802.11b/g/n
Wireless Frequency Range	2,412–2,484 MHz
Max. Transmission Power	50 mW
Max. Transmit Antenna Gain	3 dBi
Rated Voltage	DC 3.6 V
Power By	120 mAh rechargeable battery, charge through Micro USB port
Max. Power Consumption	0.2 W
Operation Distance (In Open Area)	120 m
Sensor Detection Distance	≤15 mm
Protection Class	IP20
Operating Temperature	-20–55°C
Operating Humidity	20–95% RH (non-condensing)
Color	White
Dimensions	6 x 5.7 x 1.9 cm
Weight	33 g
System Requirements	Android 5 or above / iOS 11 or above
Mounting and Used Options	 Hand-held Carry with lanyard Mount on flat surface with hook and loop fastener

Package Contents:

- » 1x SOS Button
- » 1x Lanyard
- » 1x Pin
- » 1x Hook and Loop Fastener
- » 1x User Manual

Package Information:

» Packing Dimension: 91 x 71 x 27 mm

» Packing Weight: 0.065 kg

» Carton Dimension: 435 x 300 x 500 mm

» Carton Q'ty: 250 pcs » Carton Weight: 16.58 kg





